

CELLCOM KEYCELL

Standalone GSM/4G keypad system. A great solution for security by covering those extra entrances/gates/doors.



Gate/Entrance 2
Auxiliary Keypad Unit



Gate/Entrance 3
Auxiliary Prox Unit



Gate/Entrance 4
Auxiliary Prox & Keypad Unit

Gate/Entrance 1

All devices are connected to a master unit which has a built in transmitter.



- Up to 6 auxiliary units can be connected to a master unit: Relay 1 and 2 on master unit; relays 3 to 8 on auxiliary units.
- Can have a mix of keypads & prox reader units in one set up.
- DDA LEDS on each auxiliary unit indicates correct or incorrect code/card used.
- Relay on every auxiliary unit that can be set via a dip switch.
- Keypad tones/ confirmation sound can be adjusted on auxiliary units.
- Units are wired via 5 cores of cat 5 cable. (Separate PSU depending on distances).
- 100m total cable length. An extra PSU required every 20m.

DETAILS

Power	24v d.c
Current	300mA/2A Peak 100mA Per Auxiliary Unit
Weather Rating	IP55
Relay Type	2 x N/C & N/O Contacts
Total Permanent Keypad Codes	250
Total Permanent Prox Cards	250
Time Restricted Codes/Cards	250
Temporary Codes/Cards	50

Master Units: Keypads, Prox readers with built-in transmitter.

Area code:
EU (Europe)
US (USA)
AU (Australia & NZ)



KEY-MST-PBPK-EU

Master unit with keypad & prox reader.




KEY-MST-PBK-EU

Master unit with keypad.



KEY-MST-PBP-EU

Master unit with prox reader.



Auxiliary **Pedestal** Keypads & Prox readers.



KEY-AUX-PBPK-EU

Aux pedestal unit with keypad & prox reader.




KEY-AUX-PBK-EU

Aux pedestal unit with keypad.



KEY-AUX-PBP-EU

Aux pedestal unit with prox reader.



Auxiliary Keypads & Prox readers.



KEY-AUX-IBPK-EU

Aux unit with keypad & prox reader.



KEY-AUX-IBK-EU

Aux unit with keypad.



KEY-AUX-IBP-EU

Aux unit with prox reader.

