

SOINT Multisiren Plastic Internal Sounder


Technical Specifications		
Supply	Supply Voltage:	12Vd.c (Nominal)
Siren	Output Level:	110dB A (High Sound)
	@1 metre	90dB A (Low Sound)
	Current:	300mA (High Sound)
		33mA (Low sound)
	Frequency	1.2-1.8 KHz
	Trigger	-ve
Anti-Tamper	N/C, open when cover is removed or the whole unit is removed from the wall.	
Dimensions	155mm x 100mm x 48mm	

Installation Instructions

Find a suitable location for the unit and drill a hole for the cable feed if necessary. Feed the cable through the hole in the bottom of the sounder located next to the microswitch. Drill and rawlplug the wall and secure the unit in place with the screws provided.

Note: Please allow enough space between the top of the sounder and the nearest object, to enable the lid to open.

Installation Wiring



Identify the terminals as above and connect as follows.

+12V	Positive supply from panel.
-Hi	Negative trigger from panel for high sound
-Lo	Negative trigger from panel for low sound
-LED	Negative trigger or permanent supply from panel for LED
Tamper	Anti-tamper circuit
Tamper	Anti-tamper circuit

Manufactured by:

CQR Security
125, Pasture Road, Moreton, Wirral, CH46 4TH. : Tel 0151-606-1000