

## Data Sheet

Updated 2018-11-17

### A04 Code Lock

A04 is a stand alone code lock designed for in- and outside use.



## **Functions and application**

- Compact code lock for in- and out door use in a robust metal enclosure.
- The primary advantage of the A04 is the easy to use programming mode with four function buttons on the code lock. Button 1, 2 and 3 are used to program or change the corresponding code. Button 4 is used to set the unlocking time. A six digit master code can be used to access the programming mode.
- The integrated speaker offers audible feedback when pressing buttons and programming
- The relay is a so called solid state relay that cannot be interfered with using vibrations of magnetic fields.

## Technical Data

<b>Attributes</b>	<b>A04</b>
Dimensions (HxWxD) mm	184x87x27
Housing	Metal
Mounting	Flush or surface wall mounting
Display	N
Key pad	Yes
Mifare	No
Radio 868 MHz	No
Post IR (Sweden only)	No
Built-in speaker	Yes
Exit button input	Yes
Clock input	Yes
Lockable housing	Yes
Power Supply	10-40 VDC/8-35 VAC
Electrical connection	Screw terminal
Power consumption at rest (W)	0.5
Maximum power consumption (W)	1
Current consumption at rest @12V (mA)	30
Maximum current consumption @12V (mA)	60
Current consumption at rest @24V (mA)	15
Maximum current consumption @24V (mA)	30
Maximum load (relay)	1A 30VDC
IP classification	IP55
IK classification	IK08
Temperature	-30° to + 55°C
Number of codes	3
Unlocked time	1-99 seconds
Blocked code lock	After 3 invalid entries
Day open function	No
Clock input	Yes
Article number	2-1040
E number	E5877040