

SOINT1 / SOINT2 HI-LO



A sleek white low profile louvre-free housing containing just a speaker (SOINT1), or a sounder (SOINT2), that will blend discreetly into any surrounding.

The SOINT2 HI-LO low profile housing contains a multi tone sounder, with separate inputs for exit time and alarm sound.

Options:

SOINT1/EC	16 Ohm Speaker
SOINT1/16/WH	16 Ohm Speaker, Tampered
SOINT2/WH	Electronically driven speaker, Tampered
SOINT2/WH/HI-LO	Electronically driven speaker, Tampered with selectable sound output

Specifications

	SOINT EC	SOINT1	SOINT2	SOINT2 HI-LO
Sounder type	16 Ohm speaker	16 Ohm speaker	16 Ohm speaker	16 Ohm speaker
Voltage	N/A	N/A	6 - 15 vdc	12 - 15 vdc
Current	N/A	N/A	250mA	300mA Hi / 33mA Lo
Sound output at 1m	N/A	N/A	110	110 Hi / 90 Lo
Frequency Range	N/A	N/A	1.2 - 1.8 kHz	1.2 - 1.8 kHz
Timer	N/A	N/A	N/A	N/A
Tamper protection	N/A	Wall / Cover	Wall / Cover	Wall / Cover
Material	ABS	ABS	ABS	ABS
Visual indication	N/A	N/A	LED	LED
Size	w: 100mm h: 155mm d: 48mm	w: 100mm h: 155mm d: 48mm	w: 100mm h: 155mm d: 48mm	w: 100mm h: 155mm d: 48mm



FireBrand

2Y-LINK



CQR Fire & Security
125 Pasture Road, Moreton, Wirral, CH46 4TH, UK

Sales: 0151 606 1000 Tech: 0151 606 6311 www.cqr.co.uk info@cqr.co.uk

